

PALS 9K | Tags

20120-E | Smoke Detector Transmitter

20120-E | Smoke Detector **Transmitter**

The 20120 Smoke Detector Transmitter will react to smoke by emitting a loud beep and will simultaneously transmit an alert to the Crisis Controller® software.

The 20120 is also self-monitoring, alerting the user when cleaning is needed, and automatically supervising the radio link to increase reliability. The optical chamber is replaceable, eliminating the need for factory calibration.



Features & Benefits

- Compatible with the PALS® 9000 systems and Crisis Controller® Software
- Able to transmit in the harshest RF environments
- Reliable data transmission between 60008 and LDN at a minimum of 50
- Audible beep and transmission when smoke is detected
- Long range transmission
- Constructed using heavy duty ABS plastic
- **Extended battery life** (up to 12 months depending on features and usage)
- Full transmitter supervision includes alarms for low battery and inactivity
- Returns accurate RF location and tracking information
- Easy Installation
- Clean Me" notification for when the device is in need of service
- Suitable for residential applications



Specifications

DIMENSIONS

1.6875" diameter, .625" width

CURRENT CONSUMPTION

114 mA average, dependent on programmed features

WEIGHT

12 ounces (approximate weight with transmitter attached)

OPERATING TEMPERATURE

0° to 50° Centigrade

BATTERY TYPE

3 V Lithium Battery, Duracell 123A/Panasonic 9V

ANTENNA

Internal, 900 MHz

MATERIAL

ABS Plastic

*Battery Life when deployed will vary as a function of duty time used, frequency of alarm transmissions sent, LED brightness/frequency, location broadcast interval settings and environmental conditions at your site. Based upon 240mAh CR 2032 (Energizer). Ask your Actall Sales Representative for













